PAPER • OPEN ACCESS

Boiler Temperature and Pressure Monitoring System for Thermal Power Plant through LabVIEW

To cite this article: Joshuva Arockia Dhanraj et al 2020 IOP Conf. Ser.: Mater. Sci. Eng. 988 012079

View the article online for updates and enhancements.


You may also like

- <u>Video streaming technologies using</u> ActiveX and LabVIEW M Panoiu, C L Rat and C Panoiu
- <u>Smart House Control using LabVIEW</u> S Angalaeswari, T Deepa, D Subbulekshmi et al.
- Investigation of Photovoltaic System Parameters Using LabView in Solar Irradiance Peak Condition Isdawimah, Ismujianto, Lingga Ghufira Oktariza et al.

Advancing solid state & electrochemical Society 242nd ECS Meeting

Oct 9 – 13, 2022 • Atlanta, GA, US

Presenting more than 2,400 technical abstracts in 50 symposia



ECS Plenary Lecture featuring M. Stanley Whittingham, Binghamton University Nobel Laureate – 2019 Nobel Prize in Chemistry

 \checkmark



This content was downloaded from IP address 193.146.235.209 on 03/10/2022 at 10:18

Boiler Temperature and Pressure Monitoring System for Thermal Power Plant through LabVIEW

Joshuva Arockia Dhanraj^{1*}, Kuppan Chetty Ramanathan¹, S Priyadharsini², P Jayaraman³, M Jothi Sankar²

¹Centre for Automation & Robotics (ANRO), Department of Mechanical Engineering, Hindustan Institute of Technology and Science, Chennai 603103, India. ²Department of Mechanical Engineering, Rajalakshmi Institute of Technology, Chennai 600124, Tamilnadu, India. ³Department of Mechanical Engineering, Prathyusha Engineering College, Chennai 602025, Tamilnadu, India.

* Corresponding author: joshuva1991@gmail.com

Abstract. In the ongoing processes of the thermal power plant, temperature and pressure regulation and control is important. The complete process involves two main sections, such as a temperature- and pressure sensor, which is regulated with a real-time control program and therefore employing a temperature- and pressure sensors. Within this research, a temperature sensor and pressure sensor centered on the MEMS is developed for the sensing and monitoring of temperature and pressure, along with the use of LabVIEW. This study is mainly used in the thermal plants where the high-frequency wave is being emitted. Since the wireless data transfer is being distracted by these frequencies noise this study with the help of CAN is been implemented for the information sharing and with the help of LabVIEW the process takes place in the industry can be controlled from a single monitoring room which reduces the manpower.

Keywords: Thermal power plant; temperature sensor; pressure sensor; boiler; LabVIEW

1. Introduction

This study demonstrates monitoring and controlling multiple parameters [1] of the industry using the CAN and ARM controller. The study aims at monitoring the important parameters of the boiler [2] in an industry. The parameters that are to be monitored are pressure and temperature. These parameters are taken and given to the microcontroller [3] after converting into the required formats. The microcontroller transmits the parameters to a PC. The study uses pressure and temperature sensors [4] for measuring them. Further, the parameters are taken converted into digital by a microcontroller with inbuilt ADC. The same can be received by the PC [5] and displayed in the PC for analyses. ARM controllers are selected because of their high speed [6] and complex operations. The ARM Cortex is a 32-bit processor core designed for high-performance applications in fields like automobiles, wireless networking, and industrial controls. It is based on the popular ARMv7-M processor [7] core and has been tailored for high speed and high-performance 32-bit microcontroller units. This study will use a microcontroller

Content from this work may be used under the terms of the Creative Commons Attribution 3.0 licence. Any further distribution of this work must maintain attribution to the author(s) and the title of the work, journal citation and DOI. Published under licence by IOP Publishing Ltd 1

IOP Publishing

from the Texas Instruments Stellaris series of microcontrollers based on the ARM Cortex. All these individual devices are connected using a network that employs CAN which is a long-distance serial protocol [8] and RS232 standards. The use of CAN gives the advantage that each system can be nearly 4000 feet apart but still communicate with accuracy.

Further, it provides greater immunity to the noise in an industrial environment. Further, all the obtained data and the control data are displayed on the PC which runs virtual instrumentation (VI) LabVIEW [9] which is an advanced measurement and automation software. The user-friendly control panel gives the operator to operate everything in mouse clicks whereas its robust architecture gives reliable security [10] and unmatched accuracy. VI has everything in digital so any change can be made with ease. Further, a lot of analyses such as histograms, graphs, etc. which are not possible in conventional software can be plotted on the screen. Further, the user interface has the option of user setting the threshold values thereby making the whole process entirely dynamic. So the whole system can be used for multiple machines and the parameters can be set depending upon the machine and the actual requirement. This prevents the breakdown of the machine [11] and in many cases prevents the whole industry from the shutdown. The response time is in milliseconds and so there is very little chance of error.

Ahmed Ghaly et al., [12] undertook an automated multi-sensor LabVIEW core test to incorporate a wide range of smart temperature monitoring device. This paper aims to use an auto-selected multi-sensor center in LabVIEW to incorporate a broad spectrum temperature measurement method. This multi-sensor center can be made up of a variety of different sensors and can measure multiple temperature ranges. Lazarević et al. [13] have developed a novel approach to designing the substation heating system in real-time with LabVIEW. The mathematical model of the heating substation is described in this study, which is a significant aspect of the district heating system. The key components in this paper of the heat exchanger and three-way valve from the automated control point of view are the district heating substation system. Ricman et al., [14] have done work on the development of solar collector online logging tools for vacuum control. The goal of this work is to create a program for pressurizing a solar thermoelectric hybrid device solar collector in the vacuum chamber. These experiments contributed a great deal to finalizing the aim of this work.

2. Methodology and Design

Figure 1 shows the field unit of the proposed work and Figure 2 shows the control unit design where it's connected to the pressure and temperature sensor monitoring [15] which has been controlled from a base station via LabVIEW. The CAN protocol is implemented for transmitting and receiving the signal in both the field unit and the control unit [16] in the thermal plant.

3. Interface Equipment's

The first ARM ® CortexTM-M3 based controller, ARM, is the Stellaris ® family of microcontrollers that introduces high-speed 32,000-bit computing to cost-sensitive embedded microcontroller applications. These revolutionary modules provide a 32-bit cost-efficiency equal to the legacy 8-bit and 16-bit systems in a compact footprint box. The MicroController LM3S811 is intended to work in industrial applications including monitoring and measuring equipment, plant automation, HVAC and building management, motion control, medical devices, fire and protection, and power/energy. The LM3S811 microcontroller [17] also provides the benefits of widely-accessible developer software for ARM, the IP-infrastructure application System-On-Chip (SoC), and a robust user base. Besides, the microcontroller uses the Thumb-2 compliant instruction from ARM to minimize and thus cost memory requirements. Finally, the microcontroller LM3S811 is programmed for all the members of Stellaris' large family and scalable to satisfy the exact specifications of our clients.




Figure 2. Control unit

The CAN is a typical vehicle bus system that enables the communication between microcontrollers and devices [18] in a vehicle without a host computer. It was originally developed for automobile applications but is now used in other fields as well. In this study, we are using MCP2551 [19] as a CAN transceiver. It is an 8Pin IC and It is capable of duplex CAN communication. The LM35 series are integrated precision circuit temperature sensors with a linear output valuation commensurate with the temperature of Celsius. The LM35 is incredibly easy to re-read or handle circuits with its low output impedance, a linear output, and accurate inherent adjustment. It can be used for single energy sources or more and less. Since it only pulls 60 µA from its source, its auto-heating is very low and even airs below 0.1°C. It is rated that the LM35 may work in a range of temperature from -55° C to $+150^{\circ}$ C, while the LM35C may work inside -40° C to $+110^{\circ}$ C [20] (-10° C with enhanced precision).

The Piezo Resistive Transducers series MPX5010 are state-of-the-art monolithic silicon pressure sensors designed for various applications, but particularly those with A / D inputs on a microcontroller or microprocessor. The present can be turned on or off. Relay location is double-throw switches and the present can be turned on or off. Relaxes allow for a second circuit to be entirely independent of the first circuit. For starters, a relay may be used to turn a 230V AC power circuit by a low voltage battery circuit. The interfaces are magnetic and mechanical. There are no electrical connections in the relay between the two circuits.

4. Results and Discussion

Figure 3, 4, 5, 6 shows how the LabVIEW interface is being used for monitoring the boiler. The relay circuit is used to cut the temperature source and to release the pressure when it's attained the saturation point. From Figure 3, one can see that the temperature and the pressure were maintained in the normal condition. The relay circuit and the RS232 series connections have been placed to monitor the conditions change in the vessel. The LabVIEW provides the virtual monitoring of the panel where the monitoring can be controlled through GUI. When the pressure and the temperature started to increase in the vessel,

the GUI started to show the indication of the rise in the temperature and also in pressure. In Figure 4, one can identify that the temperature and pressure exceed the maximum range the relay is being switched off as it might cause a problem inside the vessel.

Figure 5 and Figure 6 show the variations in the instability of the pressure and the temperature inside the vessel. The relay is used to monitor the changes and concerning the variations, the temperature and the pressure feed is turned on and off. The pressure and temperature were monitored through the base station have it has to be in controlled condition so these RS232 with LabVIEW helps in transmitting the information directly from the vessel to the base station. The reason behind using the wired connection is because the environmental disturbance can be neglected and the transfer rate will be high when compared to the wireless communication. This system makes the perfect monitor of the vessel and this will increase the accuracy level of the temperature and the pressure monitoring of the vessel.




Figure 3. At the beginning stage when the temperature and pressure are normal in condition

IOP Publishing





Figure 4. When the temperature and pressure exceeds the maximum range the relay is being switched off






Figure 6. Relay is being switched on after it becomes to the normal condition

5. Conclusion

As this study is being concerned the thermal power plant boiler which is been spread to a large area can be monitored and controlled by a single personal computer (PC) in which the transmission of the data is been taken with the help of CAN. The pair of CAN wires are being used in the data transfer in which the replacement of the defected is been simple. This study is mainly used in the thermal plants where the high-frequency wave is being emitted. Since the wireless data transfer is being distracted by these frequencies noise this study with the help of CAN is been implemented for the information sharing and with the help of LabVIEW the process takes place in the industry can be controlled from a single monitoring room which reduces the manpower.

6. References

- [1] Su L and Zhao Z 2011 Performance diagnosis of power plant boiler based on fuzzy comprehensive evaluation *International Conference on Electrical and Control Engineering 2011* 3076-3079.
- [2] Lian G, Niu Y, Zhang X, Lu Y and Li H 2018 Analysis of Causes of Boiler Accidents in Power Plant and Accident Handling Based on Mathematical Statistics International Conference on Engineering Simulation and Intelligent Control (ESAIC) 2018 17-20.
- [3] Ali MS and Habibullah H 2019 A review on the current status of boiler inspection and safety issues in Bangladesh *Energy Procedia* **160** 614-20.
- [4] Iturbe X, Venu B, Ozer E and Das S 2016 A triple core lock-step (TCLS) ARM® Cortex®-R5 processor for safety-critical and ultra-reliable applications 46th Annual IEEE/IFIP

International Conference on Dependable Systems and Networks Workshop (DSN-W) 2016 246-249.

- [5] Faiedh H, Farhat W, Hamdi S and Souani C 2020 Embedded Real-Time System for Traffic Sign Recognition on ARM Processor International Journal of Applied Metaheuristic Computing (IJAMC) 2020 11 77-98.
- [6] Anand S, Johnson A, Mathikshara P and Karthik R 2019 Real-time GPS tracking using serverless architecture and ARM processor 11th International Conference on Communication Systems & Networks (COMSNETS) 2019 541-543.
- [7] Abdouli AA, Bellini E, Caullery F, Manzano M and Mateu V 2019 Rank-metric Encryption on Arm-Cortex M0: Porting code-based cryptography to lightweight devices *InProceedings* of the 6th on ASIA Public-Key Cryptography Workshop 2019 23-30.
- [8] Yusoh MA, Abidin AF and Yasin ZM 2020 On-Line Classification of Excessive Neutral-to-Earth-Voltage (NTEV) Sources Using LabVIEW Software with Incorporating the Statistical-Based S-Transform and One-Versus-One SVM (OVO-SVM) Journal of Control, Automation and Electrical Systems 10 1-3.
- [9] Krishnan AR, Jayanth S and Janani R 2020 Patient Pulse Rate Monitoring System Using LabVIEW. InRecent Advances in Mechanical Engineering 557-564.
- [10] Urbikain G and de Lacalle LL 2020 MoniThor: A complete monitoring tool for machining data acquisition based on FPGA programming *SoftwareX* **11** 100387.
- [11] Prajapati P, Mishra A and Gujral R 2020 Water Level Monitoring Using IOT and Lab View *Our Heritage* **68** 1851-7.
- [12] Ghaly SM 2019 Implementation of a Broad Range Smart Temperature Measurement System Using an Auto-Selecting Multi-Sensor Core in LabVIEW Engineering, Technology & Applied Science Research 9 4511-5.
- [13] Lazarević S Čongradac V Anđelković AS Čapko D and Kanović Ž 2019 A novel approach to real-time modelling of the district heating substation system using LabVIEW *Journal of Cleaner Production* 217 360-70.
- [14] Ricman RS Szabo R and Burta A 2020 Vacuum Pressure Online Logging Software Creation for a Solar Collector 43rd International Conference on Telecommunications and Signal Processing 7 61-64.
- [15] Gong Y and Zhang P 2020 Multi-channel wireless A/D acquisition system based on NRF24L01 and LABVIEW InMATEC Web of Conferences 2020 309 01001.
- [16] Neugebauer M, Sołowiej P, Wesołowski M, Nalepa K and Hałacz J 2020 Fuzzy Model of Wind Turbine Control InRenewable Energy Sources: Engineering, Technology, Innovation 2020 541-550.
- [17] Kumaravelu R and Poornima S 2020 ARM Controller Based Smart Loom for Generating Basic Weaves. *InAdvances in Simulation, Product Design and Development 2020* 815-824.
- [18] Zang Y, Meng S, Hu L, Luo X, Zhao R, Du P, Jiao J, Huang H and Chen G 2020 Optimization Design and Experimental Testing of a Laser Receiver for Use in a Laser Levelling Control System *Electronics* 9 536.
- [19] Halder S, Conti M and Das SK 2020 COIDS: A Clock Offset Based Intrusion Detection System for Controller Area Networks InProceedings of the 21st International Conference on Distributed Computing and Networking 2020 1-10.
- [20] Chin VS, Teo PG, Ibrahim MZ, Othman WA and Wahab AA 2019 Development of Low-Cost Temperature Sensing Fan using Mapping Method on Arduino Uno and LM35 Temperature Sensor *Technical Journal of Electrical Electronic Engineering and Technology* 3 1-2.